

## FNQ time-delay 13/32" x 1-1/2" supplemental fuse

Time-delay supplemental fuse. Color code orange (500 Vac max). For superior protection, Eaton recommends upgrading to Bussmann series Limitron FNQ-R Class CC fuses. See data sheet no. 1014.



### Ratings

| Fuse amp range | IR at rated voltage | Agency information |     |
|----------------|---------------------|--------------------|-----|
|                | 500 Vac             | UL                 | CSA |
| 1/10 to 30     | 10 kA               | X                  | X   |

### Agency information

- UL Listed, Std. 248-14, Guide JDYX, File E19180, CSA Certified, C22.2 No. 248.14, Class 1422-01, File 53787, HRC-MISC, RoHS compliant, CE

| Catalog no. (amps) |            |            |        |
|--------------------|------------|------------|--------|
| FNQ-1/10           | FNQ-8/10   | FNQ-3-2/10 | FNQ-9  |
| FNQ-1/8*           | FNQ-1      | FNQ-3-1/2  | FNQ-10 |
| FNQ-15/100*        | FNQ-1-1/8  | FNQ-4      | FNQ-12 |
| FNQ-3/16           | FNQ-1-1/4  | FNQ-4-1/2  | FNQ-14 |
| FNQ-2/10           | FNQ-1-1/2  | FNQ-5      | FNQ-15 |
| FNQ-1/4            | FNQ-1-6/10 | FNQ-5-6/10 | FNQ-20 |
| FNQ-3/10           | FNQ-2      | FNQ-6      | FNQ-25 |
| FNQ-4/10           | FNQ-2-1/4  | FNQ-6-1/4  | FNQ-30 |
| FNQ-1/2            | FNQ-2-1/2  | FNQ-7      |        |
| FNQ-6/10           | FNQ-3      | FNQ-8      |        |

\* Not RoHS compliant.

### Features

- Color coded for 500 Vac maximum
- Fiber tube construction with nickel-plated brass endcaps

### Typical applications

- Motor control transformers
- Circuits with in-rush currents

Recommended blocks and holders for 13/32" x 1-1/2" fuses, see page 2-2.

## BBS fast-acting 13/32" x 1-3/8" supplemental fuse

Fast-acting supplemental fuse. Color codes black (600 Vac max 1/10 to 6 A), green (250 Vac max 7 to 10 A), purple (48 Vac max 12 to 30 A). (For superior protection, Eaton recommends upgrading to Bussmann series Low-Peak Class CC fuses. See data sheet no. 1023.



### Ratings

| Fuse amp range | IR at system voltage |         |        | Agency information |     |
|----------------|----------------------|---------|--------|--------------------|-----|
|                | 600 Vac              | 250 Vac | 48 Vac | UL                 | CSA |
| 1/10 to 6      | 10 kA                | —       | —      | X                  | X   |
| 7 to 10        | —                    | 10 kA   | —      | X                  | X   |
| 12 to 30*      | —                    | —       | —      | —                  | —   |

\* For interrupting rating, contact factory.

### Agency information

- UL Listed, Std. 248-14 (1/10-6 A@600 Vac, 7-10 A@250 Vac), Guide JDYX, File E19180, CSA Certified, C22.2 No. 248.14 (1/10-6 A@600 Vac, 7-10 A@250 Vac), Class 1422-01, File 53787, CE

| Catalog no. (amps) |            |        |        |
|--------------------|------------|--------|--------|
| BBS-1/10           | BBS-8/10   | BBS-4  | BBS-15 |
| BBS-2/10           | BBS-1      | BBS-5  | BBS-20 |
| BBS-1/4            | BBS-1-1/2  | BBS-6  | BBS-25 |
| BBS-4/10           | BBS-1-6/10 | BBS-7  | BBS-30 |
| BBS-1/2            | BBS-1-8/10 | BBS-8  |        |
| BBS-6/10           | BBS-2      | BBS-10 |        |
| BBS-3/4            | BBS-3      | BBS-12 |        |

### Features

- Color coded for 600 Vac (black) 250 Vac (green) and 48 Vac (purple) for maximum
- Fiber tube construction with nickel-plated brass endcaps

### Typical applications

- Control circuits
- Gaseous vapor fixtures
- HID ballasts
- Electronic circuits
- Hand-held meters

Recommended blocks and holders for BBS fuses, see page 2-2.

Low voltage, supplemental fuses