

SINAMICS G120 standard inverters

0.37 kW to 250 kW (0.5 hp to 400 hp)

Power Modules

Overview

PM240 Power Modules – 0.37 kW to 250 kW (0.5 hp to 400 hp), IP20 degree of protection



PM240 Power Modules, frame sizes FSA to FSGX

PM240 Power Modules have a braking chopper (four-quadrant applications) and are suitable for a large number of applications in general machinery construction.

The braking chopper is already integrated in frame sizes FSA up to FSF. For frame size FSGX, an optional pluggable Braking Module can be ordered ([see DC link components](#)).

The permissible cable lengths between inverter and motor are limited. Longer cables can be used if output reactors are connected ([see Load-side power components](#)).

Line reactors are available to minimize line harmonics as well as voltage and current peaks ([see Line-side components](#)).

Frame size FSA of the PM240 Power Module is available only without integrated line filter class A. A base filter is therefore available so that class A can be achieved. A base filter class B is also available so that class B can be achieved ([see Line-side components](#)).

Frame sizes FSB and FSC of the PM240 Power Module are available both with and without integrated line filter class A. To achieve class B, PM240 Power Modules with integrated line filter class A must be additionally equipped with a base filter class B ([see Line-side components](#)).

The PM240 Power Module is suitable for safety-oriented applications. In conjunction with a fail-safe Control Unit, the drive can be transformed into a Safety Integrated drive ([see Control Units](#)).

PM240 Power Modules in frame size FSGX (i.e. 160 kW/250 hp and higher) are currently approved only for the Safe Torque Off (STO) function.

Power Modules with integrated line filter class A are suitable for connection to TN systems. Power Modules without integrated line filter can be connected to grounded TN/TT systems and non-grounded IT systems.

Note:

Shield plates and shield connection kits are available. These can be used in the wiring installation for the Control Units and Power Modules to ensure that it complies with EMC guidelines.

[For further information, see Shield connection kits and Shield plates for Control Units and Power Modules in section Supplementary system components.](#)

SINAMICS G120 standard inverters

0.37 kW to 250 kW (0.5 hp to 400 hp)

Power Modules

Selection and ordering data

PM240 Power Modules

Rated power ¹⁾		Rated output current I _{rated} ²⁾	Power based on the base-load current ³⁾		Base-load current I _H ³⁾	Frame size	PM240 Power Module without integrated line filter	PM240 Power Module with integrated line filter class <u>A</u>
kW	hp		kW	hp				
380 ... 480 V 3 AC								
0.37	0.50	1.3	0.37	0.50	1.3	FSA	6SL3224-0BE13-7UA0	–
0.55	0.75	1.7	0.55	0.75	1.7	FSA	6SL3224-0BE15-5UA0	–
0.75	1.0	2.2	0.75	1.0	2.2	FSA	6SL3224-0BE17-5UA0	–
1.1	1.5	3.1	1.1	1.5	3.1	FSA	6SL3224-0BE21-1UA0	–
1.5	2.0	4.1	1.5	2.0	4.1	FSA	6SL3224-0BE21-5UA0	–
2.2	3.0	5.9	2.2	3.0	5.9	FSB	6SL3224-0BE22-2UA0	6SL3224-0BE22-2AA0
3.0	4.0	7.7	3.0	4.0	7.7	FSB	6SL3224-0BE23-0UA0	6SL3224-0BE23-0AA0
4.0	5.0	10.2	4.0	5.0	10.2	FSB	6SL3224-0BE24-0UA0	6SL3224-0BE24-0AA0
7.5	10	18	5.5	7.5	13.2	FSC	6SL3224-0BE25-5UA0	6SL3224-0BE25-5AA0
11.0	15	25	7.5	10	19	FSC	6SL3224-0BE27-5UA0	6SL3224-0BE27-5AA0
15.0	20	32	11.0	15	26	FSC	6SL3224-0BE31-1UA0	6SL3224-0BE31-1AA0
18.5	25	38	15.0	20	32	FSD	6SL3224-0BE31-5UA0	6SL3224-0BE31-5AA0
22	30	45	18.5	25	38	FSD	6SL3224-0BE31-8UA0	6SL3224-0BE31-8AA0
30	40	60	22	30	45	FSD	6SL3224-0BE32-2UA0	6SL3224-0BE32-2AA0
37	50	75	30	40	60	FSE	6SL3224-0BE33-0UA0	6SL3224-0BE33-0AA0
45	60	90	37	50	75	FSE	6SL3224-0BE33-7UA0	6SL3224-0BE33-7AA0
55	75	110	45	60	90	FSF	6SL3224-0BE34-5UA0	6SL3224-0BE34-5AA0
75	100	145	55	75	110	FSF	6SL3224-0BE35-5UA0	6SL3224-0BE35-5AA0
90	125	178	75	100	145	FSF	6SL3224-0BE37-5UA0	6SL3224-0BE37-5AA0
110	150	205	90	125	178	FSF	6SL3224-0BE38-8UA0	–
132	200	250	110	150	205	FSF	6SL3224-0BE41-1UA0	–
160	250	302	132	200	250	FSGX	6SL3224-0XE41-3UA0	–
200	300	370	160	250	302	FSGX	6SL3224-0XE41-6UA0	–
250	400	477	200	300	370	FSGX	6SL3224-0XE42-0UA0	–

¹⁾ Rated power based on the rated output current I_{rated} . The rated output current I_{rated} is based on the duty cycle for low overload (LO).

²⁾ The rated output current I_{rated} is based on the duty cycle for low overload (LO). These current values are valid for 400 V and are specified on the rating plate of the Power Module.

³⁾ The base-load current I_H is based on the duty cycle for high overload (HO).

SINAMICS G120 standard inverters

0.37 kW to 250 kW (0.5 hp to 400 hp)

Power Modules

Technical specifications

Line voltage 380 ... 480 V 3 AC		PM240 Power Modules				
Without integrated line filter		6SL3224-0BE31-1UA0	6SL3224-0BE31-5UA0	6SL3224-0BE31-8UA0	6SL3224-0BE32-2UA0	6SL3224-0BE33-0UA0
With integrated line filter		6SL3224-0BE31-1AA0	6SL3224-0BE31-5AA0	6SL3224-0BE31-8AA0	6SL3224-0BE32-2AA0	6SL3224-0BE33-0AA0
Output current at 50 Hz 400 V 3 AC						
• Rated current I_{rated} ¹⁾	A	32	38	45	60	75
• Base-load current I_L ¹⁾	A	32	38	45	60	75
• Base-load current I_H ²⁾	A	26	32	38	45	60
• I_{max}	A	52	64	76	90	124
Rated power						
• Based on I_L	kW (hp)	15 (20)	18.5 (25)	22 (30)	30 (40)	37 (50)
• Based on I_H	kW (hp)	11 (15)	15 (20)	18.5 (25)	22 (30)	30 (40)
Rated pulse frequency	kHz	4	4	4	4	4
Efficiency η		>0.97	>0.97	>0.97	>0.97	>0.97
Power loss at rated current	kW	0.4	0.42	0.52	0.69	0.99
Cooling air requirement	m ³ /s (ft ³ /s)	0.055 (1.94)	0.055 (1.94)	0.055 (1.94)	0.055 (1.94)	0.055 (1.94)
Sound pressure level L_{pA} (1 m)	dB	<60	<60	<60	<61	<60
24 V DC power supply for the Control Unit	A	1	1	1	1	1
Rated input current ³⁾						
• With line reactor	A	33	40	47	63	78
• Without line reactor	A	39	46	53	72	88
Length of cable to braking resistor, max.	m (ft)	15 (49)	15 (49)	15 (49)	15 (49)	15 (49)
Line supply connection U1/L1, V1/L2, W1/L3		Screw terminals	M6 screw studs	M6 screw studs	M6 screw studs	M6 screw studs
• Conductor cross-section	mm ²	2.5 ... 10	10 ... 50	10 ... 50	10 ... 50	10 ... 50
Motor connection U2, V2, W2		Screw terminals	M6 screw studs	M6 screw studs	M6 screw studs	M6 screw studs
• Conductor cross-section	mm ²	2.5 ... 10	10 ... 50	10 ... 50	10 ... 50	10 ... 50
DC link connection, connection for braking resistor DCP/R1, DCN, R2		Screw terminals	M6 screw studs	M6 screw studs	M6 screw studs	M6 screw studs
• Conductor cross-section	mm ²	2.5 ... 10	10 ... 50	10 ... 50	10 ... 50	10 ... 50
PE connection		On housing with M5 screw	On housing with M6 screw	On housing with M6 screw	On housing with M6 screw	On housing with M6 screw
Motor cable length ⁴⁾ , max.						
• Shielded	m (ft)	50 (164)	50 (164)	50 (164)	50 (164)	50 (164)
• Unshielded	m (ft)	100 (328)	100 (328)	100 (328)	100 (328)	100 (328)
Degree of protection		IP20	IP20	IP20	IP20	IP20
Dimensions						
• Width	mm (in)	189 (7.44)	275 (10.83)	275 (10.83)	275 (10.83)	275 (10.83)
• Height						
- Without integrated line filter	mm (in)	334 (13.15)	419 (16.50)	419 (16.50)	419 (16.50)	499 (19.65)
- With integrated line filter	mm (in)	334 (13.15)	512 (20.16)	512 (20.16)	512 (20.16)	635 (25.0)
• Depth						
- Without Control Unit	mm (in)	185 (7.28)	204 (8.03)	204 (8.03)	204 (8.03)	204 (8.03)
- With Control Unit	mm (in)	250 (9.84)	260 (10.24)	260 (10.24)	260 (10.24)	260 (10.24)
Frame size		FSC	FSD	FSD	FSD	FSE
Weight, approx.						
• Without integrated line filter	kg (lb)	7 (15.4)	13 (28.7)	13 (28.7)	13 (28.7)	16 (35.3)
• With integrated line filter	kg (lb)	7 (15.4)	16 (35.3)	16 (35.3)	16 (35.3)	23 (50.7)

¹⁾ The rated output current I_{rated} and the base-load current I_L are based on the duty cycle for low overload (LO).

²⁾ The base-load current I_H is based on the duty cycle for high overload (HO).

³⁾ The input current depends on the motor load and line impedance. The input currents apply for a load at rated power (based on I_{rated}) for a line impedance corresponding to $u_K = 1\%$. These current values without line reactor are specified on the rating plate of the Power Module.

⁴⁾ Max. motor cable length 25 m (82 ft) (shielded) for PM240 Power Modules with integrated line filter to maintain the limit values of EN 61800-3 Category C2.