

Power Contactors for Switching Motors

Accessories and Spare Parts for SIRIUS 3RT Contactors and SIRIUS 3RH2 Contactor Relays

Accessories

Auxiliary switch blocks, instantaneous

Additional auxiliary switch blocks		3-pole contactors			4-pole contactors				Contactor relays		
Article number	Auxiliary contacts Version	S00 3RT201	S0 to S3 3RT202, 3RT203, 3RT204, 3RT244		S00 3RT231	3RT251	S0 to S3 3RT232, 3RT233, 3RT234		3RT252, 3RT253, 3RT254	S00 3RH21	
	NO NC	10 01	11		--	--	11 11			40E 31E 22E	
		2. 3. 4. 5. 5. 6. 7. 8.	3. 4. 5. 6.		1. 2. 3. 4. 1. 2. 3. 4.		3. 4. 5. 6. 3. 4. 5. 6.			5. 6. 7. 8. 5. 6. 7. 8.	5. 6. 7. 8.
		According to EN 50012 ¹⁾			According to EN 50012 ¹⁾				According to EN 50011 ¹⁾		

Lateral auxiliary switch blocks (continued)

For sizes S00 to S3

		Left	Right									
3RH2921-□DA20	2 --			41	32	42	31	31	--	--	--	--
+ 3RH2921-□DA11	1 1											
3RH2921-□DA20	2 --			32	23	33	22	22	--	--	--	--
+ 3RH2921-□DA02	-- 2											
3RH2921-□DA11	1 1			23	14	24	13	--	--	--	--	--
+ 3RH2921-□DA02	-- 2											

For contactor relays²⁾

		Left										
3RH2921-□DA02	-- 2			--	--	--	--	--	--	42Z	33X	24
3RH2921-□DA11	1 1			--	--	--	--	--	--	51X	42X	33X
3RH2921-□DA20	2 --			--	--	--	--	--	--	60Z	51X	42X

Solid-state compatible

For size S00

		Left	Right									
3RH2911-2DE11	1 1			21	--	--	11	11	--	--	--	--
3RH2911-2DE11	1 1			32	--	--	22	22	--	--	--	--
+ 3RH2911-2DE11	1 1											

For sizes S00 to S3

		Left	Right									
3RH2921-□DE11	1 1			21	12	22	11	11	22	22	--	--
3RH2921-□DE11	1 1			32	23	33	22	22	--	--	--	--
+ 3RH2921-□DE11	1 1											

For contactor relays²⁾

		Left										
3RH2921-2DE11	1 1			--	--	--	--	--	--	51X	42X	33X

¹⁾ Combinations according to EN 50012, EN 50011 and IEC 60947-5-1 are in **bold** print. All combinations comply with EN 50005.

²⁾ Without positively driven operation.

Power Contactors for Switching Motors


Accessories and Spare Parts for SIRIUS 3RT Contactors and SIRIUS 3RH2 Contactor Relays Accessories

Auxiliary switch blocks, instantaneous

PU (UNIT, SET, M) = 1
PS* = 1 unit
PG = 41B



3RH2911-1NF..



3RH2911-2NF..



3RH2911-2DE11



3RH1921-2JE11

For contactors/ contactor relays ¹⁾	Size	Contacts Version		SD	Screw terminals		SD	Spring-type terminals	
									
Type		NO	NC	d	Article No.	Price per PU	d	Article No.	Price per PU

Solid-state compatible auxiliary switch blocks, 2-pole

- For operation in dusty atmospheres
- For solid-state circuits with rated operational currents
 $I_{th}/AC-14$ and $DC-13$ from 1 ... 300 mA at 3 ... 60 V
- Hard gold-plated contacts
- Laterally mountable auxiliary switches and auxiliary switches for snapping onto the front for 3RT2 contactors, sizes S0 to S3, are designed as mirror contacts according to IEC 60947-4-1, Appendix F.

Auxiliary switch blocks for snapping onto the front

3RT2.1, 3RT2.2, 3RT2.3, 3RT2.4	S00 ... S3	--	2		2	3RH2911-1NF02	2	3RH2911-2NF02
3RH21, 3RH24		1	1		►	3RH2911-1NF11	►	3RH2911-2NF11
		2	--		►	3RH2911-1NF20	►	3RH2911-2NF20

Lateral auxiliary switch blocks, mounting on the right and/or on the left, acc. to EN 50012

Auxiliary switch block				Left	Right		
3RT2.1	S00	1	1			--	2 3RH2911-2DE11
3RT2.2, 3RT2.3, 3RT2.4	S0 ... S3	1	1			--	2 3RH2921-2DE11
1st auxiliary switch block				Left	Right		
3RT1.5 ... 3RT1.7	S6 ... S12	1	1			►	3RH1921-2DE11
2nd auxiliary switch block				Left	Right		
3RT1.5 ... 3RT1.7	S6 ... S12	1	1			►	3RH1921-2JE11

¹⁾ For detailed information on use, see pages 3/91 and 3/93.